



**POWER BRIGHT**  
YOUR LEADER IN POWER SOLUTIONS

MODEL  
**PW1500-12**

SPECIFICATION SHEET

## 12V DC to AC 1500 Watt Power Inverter

This inverter plugs directly to a 12 Volt DC battery to power laptops, televisions, gaming consoles and other electronics and small appliances in your vehicle

**This unit has the following features:**

- 1500 watts continuous power
- 3000 watts peak power
- Provides 12.5 Amps
- Anodized aluminum case provides durability
- LED Display- Input Voltage/Output Wattage
- Built-in Cooling Fan
- Internal, Replaceable 30 Amp spade-type Fuses
- Dual 3 Prong 110 volt AC outlet
- Overload Indicator
- Power ON/OFF Switch

**CE** **RoHS**  
COMPLIANT



|                        |                            |
|------------------------|----------------------------|
| Optimum efficiency     | up to 90%                  |
| No-load draw           | < 0.4 amp (12V)            |
| Output Wave Form       | Modified Sinewave          |
| Input voltage range    | 10-15 VDC                  |
| Over voltage shutdown  | over 15 VDC                |
| Under voltage shutdown | under 10 VDC               |
| Low voltage alarm      | Audible                    |
| Overload shutdown      | Yes                        |
| Thermal shutdown       | Yes                        |
| Short circuit shutdown | Yes                        |
| AC receptacle          | 2 - three-prong receptacle |
| Warranty               | 1 year                     |
| Inverter weight        | 8.00 lbs                   |
| Dimensions (W x H x D) | 10.25 x 3.5 x 11.6 in.     |
| Weight                 | 11.5 lbs.                  |

MODEL  
**PW1500-12**  
SPECIFICATION SHEET

[www.PowerBright.com](http://www.PowerBright.com)  
© 2010 PowerBright . All rights reserved