

## PM4 SERIES

WITH STATE-OF-THE-ART 4 STAGE SMART CHARGING TECHNOLOGY AND ADJUSTABLE POWER SUPPLY MODE. POWERMAX POWER CONVERTER/BATTERY CHARGERS ARE ENGINEERED WITH THE USER AND VARIABLE ENVIRONMENTAL CONDITIONS IN MIND.

### STANDARD FEATURES INCLUDE:

- 4 STAGE SMART CHARGING
- FIXED POWER SUPPLY MODE
- VARIABLE VOLTAGE ADJUSTMENT 13Vdc To 16.5Vdc
- WORKS WITH ANY BATTERY TYPE
- LED STATUS INDICATOR LIGHT
- INTERNALLY MOUNTED COOLING FAN
- 2 YEAR WARRANTY



**P  
W  
E  
R  
M  
A  
X**

MODEL NUMBER	PM4-35-LK	PM4-45-LK	PM4-55-LK	PM4-60-LK	PM4-75-LK	PM4-100-LK
DC OUTPUT VOLTAGE (NO LOAD) APPROX.	14.6/13.6/13.2V	14.6/13.6/13.2V	14.6/13.6/13.2V	14.6/13.6/13.2V	14.6/13.6/13.2V	14.6/13.6/13.2V
MAX AMP OUTPUT CONTINUOUS	35 amps	45 amps	55 amps	60 amps	75 amps	100 amps
MAX POWER OUTPUT CONTINUOUS	510 watts	650 watts	800 watts	875 watts	1095 watts	1460 watts
MAX AC CURRENT	8 Amps	9 Amps	11 Amps	11 Amps	13 Amps	15 Amps
TYPICAL EFFICIENCY	>85%	>85%	>85%	>85%	>85%	>93%
FAN CONTROL	Proportional	Proportional	Proportional	Proportional	Proportional	Proportional
REVERSE POLARITY, OVERLOAD AND THERMAL PROTECTION	Yes	Yes	Yes	Yes	Yes	Yes
DIMENSIONS	7.8 x 9.5 x 3.5	7.8 x 9.5 x 3.5	7.8 x 9.5 x 3.5	7.8 x 9.5 x 3.5	7.8 x 9.5 x 3.5	7.8 x 9.5 x 3.5
WEIGHT	7.0 lbs	7.0 lbs	7.0 lbs	7.0 lbs	8.0 lbs	9.0 lbs

**BATTERY CHARGERS | MAINTAINERS | INVERTERS | GENERATORS  
DC POWER SUPPLIES | CONVERTERS | POWER CENTERS  
AUTOMATIC TRANSFER SWITCHES**

**20 YEARS EXPERIENCE.  
POWERMAX PM4 ARE INDUSTRY STANDARD.  
SUPPLYING OVER 20 DIFFERENT INDUSTRIES**

**(941) 201-8041  
POWERMAXCONVERTERS.COM**